



Solar Home Inverter

SHI300

Features

- ◆ 5 LED shows battery capacity more accurately
- ◆ Built-in solar controller 10A
- ◆ 4 DC output port 12V/1A
- ◆ 2 USB port 5V/1A
- ◆ 300W modified sine wave inverter



Specification

Model	SHI300
Charger Mode	PWM
PV input current	10A(max)
PV input voltage	25V(max)
Battery float voltage	13.7V ± 0.2V
Low voltage disconnection	10.7V ± 0.2V
Low voltage Reconnection	12.6V ± 0.2V
Inverter parameters	
AC output voltage	220V ± 10%
Continuous Power	300W
Output Frequency	50/60Hz ± 10%
Max optimum efficiency	>85%

